

### Claim Amendments

1. (withdrawn) A printer including a transceiver adapted to communicate with transponders, comprising:  
  
a printhead;  
  
a media conveyance adapted to transport a series of discrete media to said printhead and through a transponder operating region, at least some of said media including a transponder;  
  
a near field coupler configured to generate a near field effect to couple with the transponder for data transfer;  
  
the near field coupler having a plurality of lines electrically interconnected in parallel, and a spaced away ground plane.
  
2. (withdrawn) The printer defined by claim 1 wherein the near field coupler is formed as traces on a printed circuit board.
  
3. (withdrawn) The printer defined by claim 1 wherein the near field coupler has a characteristic impedance and the near field coupler is terminated by a terminating resistor having a different characteristic impedance.
  
4. (withdrawn) The printer defined by claim 1 wherein the plurality of lines are arranged parallel to each other.

5. (withdrawn) The printer defined by claim 1 wherein at least one of the plurality of lines has a zig-zag configuration.

6. (withdrawn) The printer defined by claim 1 wherein said printhead is positioned and configured to print on or adjacent said transponder while it is still in said transponder operating region.

7. (withdrawn) The printer defined by claim 1 wherein said printhead is positioned and configured to print on or adjacent said transponder when it is outside of said transponder operating region.

8. (withdrawn) The printer defined by claim 1 adapted to feed a web of spaced transponders through said transponder operating region, and wherein said printer communicates with a transponder located in said transponder operating region but concurrently not with another transponder located outside of said transponder operating region.

9. (withdrawn) The printer defined by claim 1, wherein the near field coupler is positioned at a minimum distance relative to the transponder whereby the presence of the transponder does not vary a characteristic impedance of the near field coupler.

10. (currently amended) A system comprising an UHF RFID transceiver and adapted to communicate exclusively with a single transponder located in a predetermined transponder operating region, said system comprising:  
a UHF near field coupler having a plurality of electrically parallel lines, the electrically parallel lines commonly coupled in series to an unmatched load;  
the UHF near field coupler having a spatially selective near field property extending into the transponder operating region;  
the system configured to establish at predetermined transceiver power levels a mutual coupling which is selective exclusively for the single transponder located in said transponder operating region.

11. (canceled)

12. (currently amended) A method of establishing communication between a UHF transceiver and a single transponder located in a predetermined confined transponder operating region, comprising:  
generating a near field in the transponder operating region, with a UHF near field coupler having a plurality of electrically parallel lines, the electrically parallel lines commonly coupled in series to an unmatched load, which varies in response to a radio frequency input signal; and  
establishing at predetermined power levels of the transceiver a mutual coupling which is selective exclusively for the single transponder located in said transponder operating region.

13. (canceled)

14. (currently amended) The method defined by claim 12, further including the step of positioning the UHF near field coupler at a distance from the transponder which does not significantly change a characteristic impedance of the UHF near field coupler.

15. (previously presented) The method defined by claim 12 including transporting a web of labels through said transponder operating region, at least some of which labels have an RFID transponder, and wherein said method includes printing on said labels.

16. (previously presented) The method defined by claim 12, further including the step of incrementally advancing the transponder within the transponder operating region, if the transponder is located at a field strength gap of the transponder operating region.

17. (withdrawn) A near field coupling device, comprising:  
a plurality of lines electrically interconnected in parallel;  
a ground plane spaced away from the plurality of lines; and  
a terminating resistor coupled to the lines, the terminating resistor selected not to match a characteristic impedance of the plurality of lines.

18. (withdrawn) The near field coupling device of claim 15, wherein the plurality of lines are formed as at least a first trace on a printed circuit board and the ground plane is formed as a second trace on a printed circuit board.

19. (withdrawn) The near field coupling device of claim 15, wherein at least one of the plurality of lines has a zig-zag characteristic.

20. (withdrawn) The near field coupling device of claim 15, wherein the plurality of lines are spatially aligned coplanar and parallel to each other.

21. (withdrawn) The near field coupling device of claim 15, wherein the length, width and interspacing of the plurality of lines is selected for a desired bandwidth.

22. (withdrawn) A near field coupler for communication with an transponder located in a transponder operating region, comprising:  
a near field coupler receiving an RF communication signal and configured to produce an array of spaced near field concentrations responsive to the RF communication signal, the spacing of said near field concentrations along a predetermined direction being significantly less than a smallest dimension of said transponder in said predetermined direction such that said transponder overlaps and is excited by a plurality of said field components when located in said transponder operating region.

23. (withdrawn) The coupler of claim 22 wherein said near field concentrations are formed by lines configured in an array with a spaced parallel geometry.

24. (withdrawn) The coupler of claim 23 wherein said lines comprise leaky edges formed in a microstrip coupler.

25. (withdrawn) The coupler of claim 23 wherein said lines have a zig-zag configuration.

26. (withdrawn) The coupler of claim 23 wherein said lines are formed as a trace on a printed circuit board having a separate ground plane.

27. (currently amended) A method for communication with a transponder, comprising the steps of:

- a) positioning a transponder in a transponder operating region with a transponder axis oriented along a predetermined direction, the smallest dimension of said transponder in said predetermined direction being significantly less than a dimension of said transponder operating region in said predetermined direction;
- b) with an RF communication signal and a UHF near field coupler having a plurality of electrically parallel lines, the electrically parallel lines commonly coupled in series to an unmatched load, forming an array of near field concentrations in said transponder operating region, said near field

concentrations extending transversely to said predetermined direction and spaced along said predetermined direction; and

c) communicating with said transponder with said RF encoding signal,

d) the spacing of said near field concentrations in said predetermined direction being significantly less than said smallest dimension of said transponder in said predetermined direction such that said transponder overlaps and is excited by a plurality of said near field concentrations when located in said transponder operating region.

28. (original) The method of claim 27, wherein a plurality of transponders are individually communicated with by sequential passage through the transponder operating region via a media conveyance.

29. (currently amended) A method for communication with an transponder comprising the steps of:

positioning the transponder over a spaced array of near field concentrations of an UHF RF communication signal from a near field coupler having a plurality of electrically parallel lines, the electrically parallel lines commonly coupled in series to an unmatched load;

the spacing of said near field concentrations being such relative to the dimensions of said transponder that said transponder overlaps and is excited by a plurality of said near field concentrations.

30. (currently amended) A method for communication with a transponder comprising the steps of:

positioning the transponder over a parallel array of leaky edges having near field concentrations of an UHF RF communication signal from a UHF near field coupler having a plurality of electrically parallel lines, the electrically parallel lines commonly coupled in series to an unmatched load; the spacing of said near field concentrations being such relative to the dimensions of said transponder that said transponder overlaps and is excited by a plurality of said near field concentrations.

31. (currently amended) A method of adaptively communicating with an transponder comprising the steps of:

positioning the transponder contiguous with a pattern of spaced near field concentrations of an UHF RF communication signal from a UHF near field coupler having a plurality of electrically parallel lines, the electrically parallel lines commonly coupled in series to an unmatched load, the pattern having at least one undesired low energy zone within which transponder communication is not optimally performed,

exciting the transponder with the near field concentrations;

confirming valid communication;

if valid communication is not confirmed, moving the transponder a distance;

repeating said exciting, confirming, and moving actions until a valid communication of the transponder is confirmed.



32. (currently amended) A method for communication with transponders having a range of sizes from smallest to largest, comprising the steps of:

- a) with an UHF RF communication signal, forming an array of spaced near field concentrations in a transponder operating region with a UHF near field coupler having a plurality of electrically parallel lines, the electrically parallel lines commonly coupled in series to an unmatched load, the spacing of said near field concentrations being less than the smaller of the length and width dimensions of said smallest transponder such that all transponders in said range of sizes overlap and are excited by a plurality of said near field concentrations when located proximate said transponder operating region;
- b) positioning proximate said transponder target sector a transponder having a size in said range of transponder sizes, and
- c) communicating with said transponder.

33. (currently amended) A method for communication with a transponder, comprising the steps of:

with an UHF RF communication signal, forming a near field concentration pattern in a transponder operating region larger than the transponder with a UHF near field coupler having a plurality of electrically parallel lines, the electrically parallel lines commonly coupled in series to an unmatched load, locating a transponder at a first position in said transponder operating region;

determining a first signal power level operationally effective to communicate with said transponder when located in said first position,  
storing said associated first power level and transponder position;  
positioning said transponder or a similar transponder in a second position in said transponder operating region;  
determining a second signal power level operationally effective to communicate with said transponder when located in said second position,  
storing said associated second power level and transponder position;  
operationally communicating with a series of transponders located in said first and second positions in said transponder operating region using the stored first and second signal power levels respectively associated with the first and second positions of transponders in said transponder operating region.

34. (original) The method of claim 33, further including the step of storing a type of the transponder.

35. (currently amended) For communicating with an RFID transponder located in a transponder operating region, a UHF near-field microstrip coupler having a plurality of electrically parallel lines, the electrically parallel lines commonly coupled in series to an unmatched load;  
the UHF near-field microstrip coupler configured to produce an array of leaky edges oriented transverse to the transponder and spaced such that said

transponder is excited by a plurality of said leaky edges when located in said  
transponder operating region.